

View 8X

The top of the line core alignment splicer

Splice Mode

Core alignment High-speed splicing and heating Large battery capacity Bright operating light Versatile fiber holder S-inch color LCD touch screen Intuitive operation with smart GUI







Pressure heater technology: Reducing heating time to only 9 seconds



Higher energy efficiency: Increased number of cycles, even with the same battery capacity



Improved lighting: For better visibility in dark environment



Versatile fiber holder: Switch between Standard and Loose-Tube fibers



Tool-free field-replaceable electrodes: Electrodes easy to replace



5,0 inch touch screen with smart GUI Highest magnification: × 520 Double tap to zoom in & out The View 8X from INNO Instrument is a first-class core alignment splicer. The X stands for "eXceed eXpectations"—and that's exactly what the View 8X does: it exceeds your expectations. The South Korean high-end manufacturer's flagship sets the benchmark for splicing efficiency. Period.

This device's features are not lacking in superlatives: Splicing time: 4 seconds. Heating time: 9 seconds. Battery power: 500 work cycles. Magnification: $520 \times .$

Plus a high-resolution 5-inch color LCD touchscreen, intuitive user interface, robust design, large memory for measured values and documentation images. The View 8X is not to be overlooked.

A decisive added value of INNO splicers is the integration into the free View Pro Cloud Management System, which enables an entirely new level of remote management. The web-based application enables onsite staff and back-office management to optimize workflows, generate comprehensive evaluations and much more:





Centralized reports and data



Optimized work and job management

Device management for calibration monitoring etc.

Specifications

Model	View 8X
Number of fibers	Single
Alignment method	Core alignment
Applicable fibers	SM (ITU-T G.652 & G.657) / MM (ITU-T G.651) / DS (ITU-T G.653) / NZDS (ITU-T G.655)
Coating diameter	100 µm to 3 mm
Cleave length	5 to 16 mm
Cladding diameter	80 to 150 μm
Splice programs	Maximal 128 modes
Heating programs	Maximal 32 modes
Typical splice loss	SM: 0.01 dB / MM: 0.01 dB / DS: 0.03 dB / NZDS: 0.03 dB / G.657: 0.01 dB
Splice time (typical) *	Quick mode: 4 seconds / SM mode 5 seconds / Auto mode: 7 seconds
Heating time	Quick mode: 9 seconds / Average: 13 seconds
Protection sleeve length	20 to 60 mm
Display	5.0" Color LCD display, Full Touch Screen
Fiber view	X, Y, XY, X/Y
Fiber display (magnification)	× 360 and × 520
Return loss	> 60 db
Data storage	Last 20,000 (values) or 10,000 (images) results
Pull test	1.96 to 2.25 N
Operation	Keys / Touchscreen
Lighting	White LED
Power supply	AC input 100 to 240 V / DC input 9 to 19 V
Battery *	Capacity: 9,000 mAh / Typical operation cycles: 500 cycles (splicing and heating)
Electrode life span	6,000 arc discharges
Data output	Cloud (View Pro Manager) and USB-C
Dimensions in mm (Height $ imes$ Width $ imes$ Depth)	162×143×158
Weight	2.68 kg

* Splicing time: measured from the time of fibers entering the screen until the estimated loss is displayed. Splicing time can vary depending on calibration status.

* Battery: Measured as a one-minute splicing and heating cycle. Measured in energy-saving mode.

Environmental conditions and resilience

Operating conditions	Altitude: 0 to 5,000 m above sea level				
	0 to 95 % relative humidity (non-dew)				
	–10 to 50 °C / Max wind 15 m/sec		\sim	\sim	
Storage conditions	0 to 95 % relative humidity (non-dew) / −40 to 80 ℃				
Water resistance (IPx2)	Rain resistance: 10 mm/h for 10 minutes				
Shock resistance	76 cm for bottom surface drop	Water	Shock resistance	Dust resistance	
Dust resistance (IP5X)	Exposure to dust: 0.1 to 500 μm diameter aluminium silicate	resistance			
Responsibility for damage resulting from misuse of the product is not accepted.					

Scope of delivery

Splicer	View 8X	Electrodes	
Cleaver	V12	Battery pack	LBT-30
SOC Holder	FH-SOC-R	Power cable	
SOC Heater cover	HTS-SOC-02	USB cable	USB-7P
AC Adapter	JS-180300	Carrying case	
Cooling tray	CG-23	Shoulder strap	ST-01

Accessories

In addition to the splicer, various tools are required for the correct preparation of the fibers. If you are not yet equipped for this, we are of course happy to help. Whether it's a suitable stripper, a loose tube cutter, cleaning fluid and cloths or a crimping press, we can provide everything. And we're here to help and advise you. Talk to us or get an initial overview online.

The information in this catalog is subject to change without notice.

KWS Electronic Test Equipment GmbH Tattenhausen · Raiffeisenstraße 9 · 83109 Großkarolinenfeld Phone 00 49 .(0) 80 67 .90 37-0 · Fax 00 49 .(0) 80 67 .90 37-99 info@kws-electronic.de · www.kws-electronic.com shop: www.kws-electronic.shop



Splicing technology on our website: www.kws-electror

